

GM DIGITAL MIXER M24 Plus



SPECIFICATION

- 24 MIC/ LINE input, 2 sets of 3.5 Lotus stereo input, 1 set of 3.5 stereo earphone input interface. 2 sets of digital input: sound card, MP3, AES digital input
- Two 16 in and 8 out stage interface boxes can be connected at the same time to realize I/O IO expansion and maximum support 66 signal inputs, 36 signal outputs
- Compatible with DANTE protocol, realize the audio signal through the switch for input/output routing
- 8*8 multi-channel playback recording function
- 13 DCA marshals, 13 mute marshals
- Built-in signal generator (pink noise/positive wave/white noise) with optional Bluetooth 5.0 lossless digital playback
- Each input is 5-segment parameter EQ adjustable, arbitrary high-low pass filter frequency division
- With sound card /MP3, support U disk /PC end playback, recording
- Odd-even channel stereo modulation function (LINK)
- Input channel independent feedback suppressor function
- Integrated RTA real-time spectrum display function
- 20 channels mixing signal output, AES output
- Each output is 15 sections of parameter EQ adjustable (main output is 31 sections), high and low pass Filter arbitrary frequency division
- Built-in 4-channel independent effector, using French DREAM professional effect DSP chip
- Integrated automatic mixing function
- Chinese and English interface display, PC/iPad/ Android wireless remote control
- 26 100mm, ALPS high-precision electric push
- Linux operating system, non-Android system, no crash and no virus interference
- 10.1" 1280*800 HD capacitive touch screen display
- RS232 central control on line control

M24 Plus



Location

14, Woods Road,
Chennai - 600002
Tamil Nadu, India.

Email

gmgiri14@gmail.com
info@gmaudio.co.in
gmgiri@gmaudio.co.in

Phone

044 - 28613223

Mobile

98840 31505